

TRADE TRAINING ATC PROGRAMME

ELECTRICIAN GENERAL

www.iqbalkalmati.blogspot.com












GOVERNMENT OF THE PUNJAB
TECHNICAL EDUCATION & VOCATIONAL TRAINING AUTHORITY
PUNJAB BOARD OF TECHNICAL EDUCATION
TRADE TESTING CELL, LAHORE.

T.T.P. Series No. 22

Price Rs. 25/-







مزید کتب پڑھنے کے لئے آج ہی وزٹ کریں : www.iqbalkalmati.blogspot.com

		
1 STRIPPING	2 STRIPPING	3 INSTRUCTION SHEET
		
4 INSTRUCTION SHEET	5 SOLDERING	6 WELDING
		
7 TERMINAL BOX	8 CABLE BOX	9 CABLE DISTR. PLUG
LAYOUT		EP 2.1/3.5.5/ Cable jointing
DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING FOR GERMAN TECHNICAL TRAINING PROGRAMME		ELECTRICIAN GENERAL

SEQUENCE OF OPERATION

1. In order to ease working and ensure greater reliability, place end of cable on some suitable support (e.g. trestle), and mark the length to be off-set.
2. Secure jute with wire or insulant winding.
See instr. sheet No. EP/2.3/3.5.5/3
3. Incise and peel jute sheathing.
4. File steel-tape armouring bare for 20 to 30 mm and tin.
5. Place wire winding on tinned steel-tape armouring (some 10 windings).
6. Incise armouring in front of winding by filing all around with triangular file and remove by nicking.
Note: Saw must not be used.
7. Heat with blow-lamp and peel-off the impregnated and well-adhesive paper sheath. (e.g. with petroleum)
8. Scrape bare and tin lead jacket for some 20 to 30 mm next to wire winding.
9. Loop one half of ground wire in 2 windings around armouring and lead jacket.
10. Join the three windings by bead soldering.
See instr. sheet No. EP/2.3/3.5.5/3



STRIPPING OF ARMoured CABLES

EP 2.3/3.5.5/1

Cable jointing



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME


ELECTRICIAN

GENERAL

SEQUENCE OF OPERATION

11. Notch the lead sheath all around to the required length, then notch again all around according to the set-off length of the joint wire sheath (belt).

The lead sheath section between the two notches serves as protection of the remaining belt and is removed later. (see Step 18)



12. Crack two closely parallel longitudinal cracks and reel off intermediate strip with flat-nosed pliers or strip reeler.




13. Turn up lead sheath and tear off at notch (do not cut).

14. Reel off and tear off joint wire sheathing (belt).



15. Cut off filler with knife from inside to outside. Do not cut against wires.

16. Lace wires with (impregnated) twine according to connecting length. See instr. sheet No.2.3/3.5.5/4



17. Strip wires to windings, whereby the outer layers should be notched and the inner layers torn.

18. Remove remaining lead sheath (belt) and expand end of lead sheathing to funnel.



19. Lace exposed joint wire sheathing (belt) by winding with (impregnated) binder twine. See instr. sheet No.2.3/3.5.5/4



STRIPPING OF ARMoured CABLES

EP 2.3/3.5.5/2

Cable jointing



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GENERAL

WIRE WINDINGS

SEQUENCE OF OPERATION

1. Bend wire right angularly and loop around the cable.
2. Wind several layers tightly and securely over loop.
3. Twist and cut wire ends.




TINNING OF LEADEN WORK-PIECES

SEQUENCE OF OPERATION

1. Clean and scrape work-pieces bare.
2. Spread flux on work-piece.
3. Heat carefully while moving flame back and forth (simultaneously).
4. Melt solder (rod tin).
5. Heat the applied solder only to a pasty condition (it must not flow) and spread with flux-soaked cloth.

Note

The back and forth movement of the flame during the heating of the work-piece is necessary for preventing localized overheating (melting of the lead).



INSTRUCTION SHEET

EP 2.3/3.5.5/3

Cable jointing



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GENERAL

TWINE WINDING WITH THREADED END

SEQUENCE OF OPERATION

1. Loop end of twine and start winding just before end of insulation.
2. Loop twine in several closely adjacent firm windings and thread end through loop.
3. Cut ends of twine.



TWINE WINDING WITH KNOTTED END

SEQUENCE OF OPERATION

1. Crease end of twine and wind some three layers around crease.
2. Push winding under knurled cable jacket, tighten slightly and continue winding.
3. Knot and cut ends.



Note:

Windings are made of tape, twine or wire, depending on the purpose and composition of the line to be laced. They must be smooth and uniform, firm and unshiftable.

INSTRUCTION SHEET

EP 2.3/3.5 5/4

Cable jointing



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GENERAL

SEQUENCE OF OPERATION

1. Strip line to required length
(= length of sleeve + 10 mm);
Clean conductor if necessary.



2. Push stripped end into the sleeve.

3. Protect insulation from soldering heat, e.g. by lacing with asbestos yarn.




4. Put cable and cable-lug in vertical position.

5. Coat soldering point with paste flux.



6. Solder, heat cable-lug above the soldering point, permit solder to penetrate into sleeve by knocking.

7. Insulate and secure and protect by lacing, if this should be required.



Note:

The solder must fill the sleeve of the cable-lug completely, but must not penetrate any further.

Only solders containing a minimum of 40% tin should be used.

MOUNTING LARGE CABLE-LUGS BY SOLDERING

EP 2.3/3.5.5/5
Cable jointing



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GENERAL


The Preliminaries for welding cable-lugs on aluminium conductors require particularly meticulous execution, so as to ensure that the actual welding be rapid and reliable.

Working Steps


1. Set-off and strip cables to required length and form out the conductors.



2. Smooth cut conductor ends by cutting followed by subsequent cleaning (use benzine on cable cores). Form round segmental conductor beforehand.




3. Attach cable-lugs. Fill hole of cable-lug with pointed wires from waste conductor ends completely.



4. Place conductor and cable-lug in vertical position, and attach welding form with flash guard if this is required.

5. Coat points to be welded with suitable flux. The flux must not be hygroscopic after cooling.

6. Coat filler with flux and prepare.



Note

The fillers used should preferably be waste ends of the cable core to be welded.

WELDING CABLE-LUGS ON ALUMINIUM CONDUCTORS

EP 2.3/3.5.5/6

Cable jointing



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN


GENERAL 8

SEQUENCE OF OPERATION

1. Set welding flame pointedly and at low-oxygen (excess of gas).
2. Heat conductor end with pointed flame circulatingly until lugs are formed on the faces of the individual wires.
3. Spread lugs together with filler. Heat rim of cable-lug until its surface bulges.
4. Spread the conductor and lug melts together. Build up filler until a lug is formed.
In building up the lug feed filler to the melt and continue to feed while stirring.
Take off filler before removing flame.
5. Permit melt to harden and clean cable-lug.
6. Wrap cable end.

Note

The welding must be performed rapidly.



WELDING CABLE-LUGS ON ALUMINIUM CONDUCTORS

EP 2.3/3.5.5/7

Cable jointing





DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GENERAL





CABLE-CONNECTING BOX

EP 23/3.5.5/9
Cable jointing




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GENERAL



CABLE DISTRIBUTION PLUG











EP 2.3/3. 5.5/10




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

		
1 KITCHEN INSTALLATION	2 DRAWING ROOM INST.	3 SLEEPING ROOM INST.
		
4 HALL INSTALLATION	5 IMPULSE SWITCH INST.	6 TREMBLER BELL INST.
		
7 TIME SWITCH INST.	8 INDICATOR BELL INST.	9 TIMING SWITCH INST.
LAYOUT		EP 2.1/3.5.4/
		Installation II
 DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING PAK-GHAN TECHNICAL TRAINING PROGRAMME		ELECTRICIAN GENERAL 13



Material:

- 1 Fuse, (complete)
- 2 Junction boxes
- 2 Lampholders
- 2 Single pole switches
- 1 Socket (Schuko or 3-pin)

For Alteration:

- 2 Sockets (Schuko or 3-pin)

Use instead of

- 2 Single pole switches
- 1 Multicircuit switch

According to the type of installation

Screws, clamps, cables, pipes, wire, batten or casing and capping material

- a) CASING and CAPPING
- b) BATTEN WIRING
- c) PIPE WIRING
- d) CABLE WIRING

Estimate the material required for the installation

- a) Switch 1 operates lamp 1, switch 2 operates lamp 2
- b) Alteration, remove switch 1 + 2, replace number 1 with a multi-circuit switch, number 2 with a socket (Schuko or 3-pin)

Draw complete wiring- and current path diagrams of above shown installation layout and alteration thereof.

DO NOT cut off spare wires in junction boxes, switches etc.

Check and connect SUPPLY in PRESENCE of your INSTRUCTOR.

KITCHEN

EP 2.3/3.5.4/1

Installation II




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GENERAL



MATERIAL:

- 1 Fuse, (complete)
- 2 Junction boxes
- 3 Lampholders
- 1 Socket (Schuko or 3-pin)
- 1 Single pole switch
- 1 Multicircuit switch

According to the type of installation

Screws, clamps, cable, pipes, wire, batten or casing and capping material

- a) CASING and CAPPING
- b) BATTEN WIRING
- c) PIPE WIRING
- d) CABLE WIRING

Indicate number of wires in above given installation layout.

Estimate the material required for the installation.

Draw complete wiring- and current path diagrams of above shown installation layout.

Check and connect SUPPLY in PRESENCE of your INSTRUCTOR.

DRAWING/LIVING ROOM

EP 2.3/3.5.4/2

Installation II




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GENERAL



MATERIAL:

- 1 Fuse, (complete)
- 2 Junction boxes
- 2 Lampholders
- 1 Socket (Schuko or 3-pin)
- 1 Change-over switch (pull)
- 1 Change-over switch

According to the type of installation

Screws, clamps, cable, pipes, wire, batten or casing and capping material

- a) CASING and CAPPING
- b) BATTEN WIRING
- c) PIPE WIRING
- d) CABLE WIRING

Indicate number of wires in above given installation layout.

Estimate the material required for the installation.

Draw complete wiring- and current path diagrams of above shown installation layout.

Check and connect SUPPLY in PRESENCE of your INSTRUCTOR.

SLEEPING ROOM


EP 2.3/3.5.4/3
Installation II



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL



MATERIAL:

- 1 Fuse, (complete)
- 2 Junction boxes
- 2 Lampholders
- 2 Change-over switches
- 1 Intermediate switch
- 1 Socket (Schuko or 3-pin)

According to the type of installation

Screws, clamps, cables, pipes, wire, batten or casing and capping material

- a) CASING and CAPPING
- b) BATTEN WIRING
- c) PIPE WIRING
- d) CABLE WIRING

Indicate number of wires (conductors) in above given installation layout.

Estimate the material required for the installation.

Draw complete wiring- and current path diagrams of above shown installation layout.

Check and connect SUPPLY in PRESENCE of your INSTRUCTOR.

If intermediate switch is not available then perform practical exercise of Drg.No. EP/2.3/3.5.4/10

HALL

EP23/3.5.4/4

Installation II




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GENERAL



MATERIAL:

- 1 Fuse, (complete)
 - 1 Impulse switch
 - 2 Lampholders
 - 3 Momentary contact switches
- According to the kind of installation
- Screws, clamps, cable, pipe and wires, casing and capping material, batten material

- a) CASING and CAPPING
- b) BATTEN WIRING
- c) PIPE WIRING
- d) CABLE WIRING

Estimate the material required for the installation to be made.

Draw complete wiring and current path diagrams of above shown installation layout.

Check and connect in PRESENCE of your INSTRUCTOR.

If impulse switch is not available then perform practical exercise of Drg.No. EP/2.3/3.5.4/11

IMPULSE SWITCH

EP 2.3/3.5.4/5

Installation II




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GENERAL



MATERIAL:

- 1 Fuse, (complete)
- 1 Transformer 220/8 V
- 3 Trembler bells
- 3 Momentary contact switches, single
- 3 Momentary contact switches with name plate
- According to the kind of installation
- 4 Junction boxes, screws, clamps, cable, pipes and wire, casing and capping material.

- a) CASING and CAPPING
- b) BATTEN WIRING
- c) PIPE WIRING
- d) CABLE WIRING

Estimate the material required for the installation to be made.

Draw complete wiring- and current path diagrams of above shown installation layout.

Check and connect SUPPLY in PRESENCE of your INSTRUCTOR.

If 8V bell is not available then perform this exercise without Transformer at 220V

TREMBLER BELL

EP 2.3/3.5.4/6

Installation II




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GENERAL



MATERIAL:

- 1 Fuse, (complete)
- 1 Time switch
- 3 Lampholders
- 3 Momentary contact switches

According to the kind of installation

- 4 Junction boxes, screws, clamps, cable, pipes and wires, casing and capping material, batten material.

- a) CASING and CAPPING
- b) BATTEN WIRING
- c) PIPE WIRING
- d) CABLE WIRING

Estimate the material required for the installation to be made.

Draw complete wiring- and current path diagrams of above shown installation layout.

Check and connect SUPPLY in PRESENCE of your INSTRUCTOR.

TIME SWITCH

EP 2.3/3.5.4/7

Installation II




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GENERAL

20



MATERIAL:

- 1 Fuse, (complete)
- 1 Transformer 220/8 V
- 1 Number-Indicator 8 Nos.
- 1 Trembler bell
- 8 Momentary contact switches
- According to the kind of installation
- 5 Junction boxes, screws, clamps, cable, pipes and wires, casing and capping material, batten material.

- a) CASING and CAPPING
- b) BATTEN WIRING
- c) PIPE WIRING

Estimate the material required for the installation to be made.

Draw complete wiring-and current path diagrams of above shown installation layout.

Check and connect SUPPLY in PRESENCE of your INSTRUCTOR.

If 8V bell indicator is not available then perform this exercise without Transformer at 220V.

INDICATOR BELL


EP 2.3/3.5.4/8
Installation II



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL



MATERIAL:

1 Fuse, (complete)

3 Lampholders

4 Junction boxes

1 Timing switch

According to the kind of installation

screws, clamps, cable, pipes and wire, casing and capping material.

For extension of exercise

1 Contactor

1 Fluorescent Lamp, (complete)

a) CASING and CAPPING

b) BATTEN WIRING

c) PIPE WIRING

d) CABLE WIRING

Estimate the material required for the installation to be made.

Draw complete wiring- and current path diagrams of above shown installation layout.

a) without extension

b) with extension

Check and connect SUPPLY in PRESENCE of your INSTRUCTOR.

TIMING SWITCH

EP 2.3/3.5.4/9

Installation II




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GENERAL

22



Estimate the material required for the installation to be made

- a)
- b)
- c)
- d)

Draw complete WIRING- and CURRENT PATH DIAGRAM of above shown INSTALLATION-LAYOUT.

CHECK AND CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

FLUORESCENT LAMPS WITH ONE BALLAST


EP 2.3/3.5.4/10
Installation II



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAX-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL










Estimate the material required for the installation to be made

- a)
- b)
- c)
- d)

CHECK AND CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

	FLUORESCENT LAMPS WITH TWO BALLAST	EP 2.3/3.5.4/11 Installation II
	DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING PAK-GERMAN TECHNICAL TRAINING PROGRAMME	ELECTRICIAN GENERAL
		24

		
1 ON AND OFF CIRCUIT	2 OVER CURRENT PROTECTION	
		
3 INTERLOCKING BY SWITCHES	4 INTERLOCKING BY CONTACTORS	
		
5 SEQUENCE CONTROL HAND DRIVEN	6 SEQUENCE CONTROL TIME RELAY DRIVEN	
LAYOUT		EP 1.1/2.5.3/ Circuits
DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING PAK-GERMAN TECHNICAL TRAINING PROGRAMME		ELECTRICIAN GENERAL 25



Implementation of a control- and power circuit

Implement the control- and power circuit on the switch panel of the exercise table.

Check the circuit thoroughly.

Voltage is to be applied by the instructor.

Sequence of testing the functions:

1. Press momentary switch b 2
2. Release momentary switch b 2
3. Press momentary switch b 1
4. Release momentary switch b 1

Describe your observations in brief with your own words.

Note: Auxiliary contact c1, that is no-contact of contactor c1, has to be parallel to the closer contact of momentary switch b2.

ON-AND OFF CIRCUIT WITH CONTACTOR

EP 13/2.5.3/1

Circuits




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

27



Implementation of a control- and power circuit

Implement the control- and power circuit on the switch panel of the exercise table.

Check the circuit thoroughly.

Voltage is to be applied by the instructor.

Test the functions as follows:

1. Adjust the electrothermic overcurrent release to the rated current of the motor.
2. Remove one connection to the three phase motor and operate single pole switch b1.
3. Measure the time until the overcurrent release works, that means until control-lamp h1 lights up.
4. Switch off b1.
5. Establish the proper connection to the three phase motor and unlock the thermic overload protection.
6. Switch on b1 and after some time switch off.

Describe your operations in brief.

Note: Contacts of the electro-thermic overload protection have to be in series with the off-switch.

TESTING THE ELECTRO-THERMIC OVERCURRENT PROTECTION

EP 13/2.5.3/2

Circuits




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

28



Implementation of a control- and power circuit

Implement the control- and power circuit on the switch panel of the exercise table.

Check the circuit.

Voltage is to be applied by the instructor.

1. Press momentary switch b2 and release it.
2. Press momentary switch b1 and release it.
3. Press momentary switch b3 and release it.
4. Press momentary switch b1 and release it.
5. Press momentary switch b3 and release it.
6. Press momentary switch b2 and release it.
7. Press momentary switch b1 and release it.
8. Press momentary switches b2 and b3 simultaneously.
9. Switch off by momentary switch b1.

Describe your observations in brief.

Note: Momentary switches with opener and closer contacts connected in opposite branches are used to allow only one contactor at the same time to work.

INTERLOCKING BY SWITCHES

EP 1.3/2.5.3/3

Circuits -




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

29



Implementation of a control- and power circuit

Implement the control- and power circuit on the switch panel of the exercise table.

Check the circuit thoroughly.

Voltage is to be applied by the instructor.

Sequence of testing the functions:

1. Press momentary switch b2 and release it.
2. Press momentary switch b3 and release it.
3. Press momentary switch b1 and release it.
4. Press momentary switch b3 and release it.
5. Press momentary switch b2 and release it.
6. Press momentary switch b1 and release it.
7. Press momentary switch b2 and release it.

Describe your observations in brief.

Note: If it is demanded that only one contactor can work at the moment then there has to be a nc-auxiliary-contact in series with each opposite contactor.

A combination of both interlocking systems (exercises 4 and 5) will increase the function.

INTERLOCKING BY CONTACTORS

EP 1.3/2.5.3/4

Circuits




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

3c



Implementation of a control- and power circuit

Implement the control- and power diagram on the switch panel of the exercise table.

Check the circuit thoroughly.

Voltage is to be applied by the instructor.

Sequence of testing the functions:

1. Press momentary switch b3 and release it.
2. Press momentary switch b2 and release it.
3. Press momentary switch b3 and release it.
4. Press momentary switch b1 and release it.

Describe your observations in brief.

Note: A no-auxiliary-contact of contactor c1 before contactor c2 means that contactor c2 only can be driven after contactor c1 has been operated.

SEQUENCE CONTROL HAND DRIVEN

EP 13/2.5.3/5

Circuits




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

31



Implementation of a control- and power circuit

Implement the control- and power circuit on the switch panel.

Check the circuit.

Voltage is to be applied by the instructor.

Sequence of testing the functions:

1. Press momentary switch b2 and release it.
2. Observe the sequence of starting of the motors.
3. Press momentary switch b1 and release it.
4. Adjust another time of the time relay and start again with momentary switch b2.

Note: This given circuit is similar to the circuit of exercise 5, but it is working automatically due to auxiliary contactor d1.

SEQUENCE CONTROL TIME RELAY DRIVEN

EP13/2.5.3/6

Circuits



















DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

32

			
1 DC - SERIES MOTOR	2 DC - SHUNT MOTOR	3 DC - COMPOUND MOTOR	4 SWITCH, ON-OFF
			
5 SWITCH, REVERSING	6 SWITCH, Δ	7 SWITCH, Δ Δ REVERSING	8 SWITCH, MULTI SPEED
			
9 CONTACTOR ON-OFF	10 CONTACTOR ON-OFF	11 CONTACTOR ON-OFF	12-13-14 CONTACTOR REV-
			FOR POWER CIRCUITS 12, 15, 18, 21, THERE ARE SEPARATE CURRENT PATH AND WIRING DIAGRAMS (13-14, 16-17, 19-20, 22-23.) ALL EXERCISE SHEETS MAY BE USED FOR IN- STALLATION AS WELL AS FOR PLUG WIRING EXERCISES.
15-16-17 CONTACTOR Δ	18-19-20 CONTACTOR Δ Δ REV	21-22-23 CONT. MULTI SPEED	
LAYOUT			EP 1.1/3.5.1/ Motors & Switches Contactors, Circuits
 DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING PAK-GERMAN TECHNICAL TRAINING PROGRAMME			ELECTRICIAN GENERAL
			33

CLOCKWISE

A	F	H/B	E
O	O	O	O

DRAW CONNECTIONS AND
LINKS FOR CLOCKWISE AND
ANTI-CLOCKWISE DRIVE

ANTI-CLOCKWISE

A	F	H/B	E
O	O	O	O

a.) MARK FLOW OF CURRENT AND DIRECTION OF MOTOR ROTATION (arrow head)

b.) GIVE NAME OF COMPONENTS ON DOTTED LINES

c.) WHAT MEASURES CAN BE TAKEN TO INCREASE OR DECREASE THE SPEED/POWER

d.) TAKE SUITABLE MATERIAL AND DO YOUR PRACTICAL JOB.

e.) WHAT RULES CAN YOU APPLY TO DETERMINE THE FLOW (Direction) OF CURRENT?

	<p>SERIES WOUND D.C MOTOR</p>	<p>EP 1.3/3.5.W1</p> <p>Motors&Switches</p>
	<p>DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING</p> <p>PAK-GERMAN TECHNICAL TRAINING PROGRAMME</p>	<p>ELECTRICIAN GENERAL</p> <p>36</p>

CLOCKWISE

A	D	H/B	C
O	O	O	O

DRAW CONNECTIONS AND
LINKS FOR CLOCKWISE AND
ANTI-CLOCKWISE DRIVE

ANTI-CLOCKWISE

A	D	H/B	C
O	O	O	O

a.) MARK FLOW OF CURRENT AND DIRECTION OF MOTOR ROTATION (arrow head)

b.) GIVE NAME OF COMPONENTS ON DOTTED LINES.

c.) WHAT MEASURES CAN BE TAKEN TO INCREASE OR DECREASE THE SPEED/POWER.

d.) TAKE SUITABLE MATERIAL AND DO YOUR PRACTICAL JOB.

e.) WHAT RULES CAN YOU APPLY TO DETERMINE THE FLOW (Direction) OF CURRENT?

	SHUNT WOUND D.C. MOTOR	EP 1.3/3.5.1/2
		Motors & Switches
	<p>DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING</p> <p>PAK-GERMAN TECHNICAL TRAINING PROGRAMME</p>	<p>ELECTRICIAN</p> <p>GENERAL</p>

37

CLOCKWISE

A	F	H/B	E
D	C		

ANTI-CLOCKWISE

A	B	H/B	E
D	C		


COMPOUND WOUND DC MOTOR

DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN GENERAL

38



TAKE SUITABLE MATERIAL AND DO YOUR PRACTICAL JOB.

ACCORDING TO INSTRUCTORS DECISION PLUG WIRING OR BOARD INSTALLATION EXERCISE.

CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

ON-OFF DRUM SWITCH

EP 1.3/3.5.1/4

Motors & Switches




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

39



TAKE SUITABLE MATERIAL AND DO YOUR PRACTICAL JOB.

ACCORDING TO INSTRUCTORS DECISION PLUG WIRING OR BOARD INSTALLATION EXERCISE.

CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

REVERSING DRUM SWITCH

EP 13/3.5.1/5

Motors & Switches




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

40



TAKÉ SUITABLE MATERIAL AND DO YOUR PRACTICAL JOB.

ACCORDING TO INSTRUCTORS DECISION PLUG WIRING OR BOARD INSTALLATION EXERCISE.

CONNECT SUPPLY IN PRESENCE OR YOUR INSTRUCTOR.

STAR-DELTA REVERSING DRUM SWITCH

EP 1.3/3.5.1/7

Motors&Switches





DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

42





TAKE SUITABLE MATERIAL (MOTOR) AND DO YOUR PRACTICAL JOB.
EXERCISE SHEET NO. 3.5.1/10 AND 3.5.1/11 MAY BE USED IN ADDITION.

ACCORDING TO INSTRUCTORS DECISION PLUG WIRING OR BOARD INSTALLATION.
CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.
DRAWING IS ALSO USED FOR EXERCISE EP 2.3/4.5.1/5

MOTOR CONNECTION, 3~ ON-OFF

EP 1.3/3.5.1/9

Contactors




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

44



IF THIS IS GIVEN IN A DRAWING IT HAS TO BE BELOW THE CONTACTOR CONCERNED WITH.

DESCRIPTION OF PARTS:

- b0 PUSH BUTTON-OFF MOMENTARY CONTACT
- b1 PUSH BUTTON-ON
- c1 AUTOMATIC CONTACTOR (COIL)
- e1 CONTROL CIRCUIT FUSE
- e2 THERMAL OVERLOAD SWITCH WITH LOCK
- h1 WARNING LAMP (OVERLOAD)
- h2 CONTROL LAMP (MOTOR RUNNING)

FOR MAIN CONTACTS
 FOR "CLOSER" or MAKE CONTACTS
 FOR "OPENER" or BREAK CONTACTS
 PATH WHERE YOU WILL FIND THE CONTACTS IN THE DRAWING

ALL CONTACTS CONTROLLED OF e.g. CONTACTOR c1 ARE ALSO MARKED WITH c1

- a) WORK OUT YOUR DESCRIPTION OF CONTROL CIRCUITS 3.5.1/0
 - b) TAKE SUITABLE MATERIAL AND DO YOUR PRACTICAL JOB.
- EXERCISE SHEET No. 3.5.1/09 AND 3.5.1/11 MAY BE USED IN ADDITION.
 ACCORDING TO INSTRUCTORS DECISION PLUG WIRING OR BOARD INSTALLATION EXER.
 CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

DRAWING IS ALSO USED FOR EXERCISE EP 2.3/4.5.1/5

MOTOR CONNECTION, ON-OFF


EP 1.3/3.5.1/10
 Contactors



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
 GENERAL



* TAKE SUITABLE MATERIAL AND DO YOUR PRACTICAL JOB.
EXERCISE SHEET No. 3.5.1/09 AND 3.5.1/10 MAY BE USED
IN ADDITION.

RECORD MOTOR DATA

CHECK WITH A.-METER * AND
RECORD STARTING AMPS. A

MOTOR NAME PLATE

V A

RUNNING AMPS. A

SAME MOTOR SHOULD BE USED FOR STAR-DELTA CONNECTION EXERCISE.

3 PHASE ON-OFF
WITH CONTROL LAMPS

EP 1.3/3.5.1/11

Circuits III




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

46



MOTOR CONNECTION, 3~ REVERSING

EP 1.3/3.5.1/12

Contactors




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

47



TAKE SUITABLE MATERIAL AND DO YOUR PRACTICAL JOB.
EXERCISE SHEET No. 3.5.1/12 AND 3.5.1/13 MAY BE USED IN ADDITION.
ACCORDING TO INSTRUCTORS DECISION PLUG WIRING OR BOARD INSTALLATION.
CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

NOTE : DO NOT SWITCH DIRECTLY FROM ONE DIRECTION TO THE OTHER, ALLOW MOTOR TO STOP.

DRAWING IS ALSO USED FOR EXERCISE EP 2.3/4.5.1/6

3 PHASE REVERSING WITH CONTROL LAMPS

EP 1.3/3.5.1/14

Circuits III




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME


ELECTRICIAN
GENERAL


49



TAKE SUITABLE MATERIAL (MOTOR) AND DO YOUR PRACTICAL JOB.
 EXERCISE SHEET No. 3.5.1/16 AND 3.5.1/17 MAY BE USED IN ADDITION.
 ACCORDING TO INSTRUCTORS DECISION PLUG WIRING OR BOARD INSTALLATION.
 CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

DRAWING IS ALSO USED FOR EXERCISE EP 2.3/4.5.1/7

	MOTOR CONNECTION, 3~ STAR-DELTA	EP 1.3/3.5.1/15 Contactors
	DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING PAK-GERMAN TECHNICAL TRAINING PROGRAMME	ELECTRICIAN GENERAL 50



a.) WORK OUT YOUR DESCRIPTION OF CONTROL CIRCUITS 3.5.1/0
 b.) TAKE SUITABLE MATERIAL (MOTOR) AND DO YOUR PRACTICAL JOB.
 EXERCISE SHEET NO 3.5.1/15 AND 3.5.1/17 MAY BE USED IN ADDITION.
 ACCORDING TO INSTRUCTORS DECISION PLUG WIRING OR BOARD INSTALLATION.

CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

DRAWING IS ALSO USED FOR EXERCISE EP 2.3/4.5.1/7

MOTOR CONNECTION, 3~ STAR-DELTA

EP 1.3/3.5.1/16

Contactors




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

51



TAKE SUITABLE MATERIAL (MOTOR) AND DO YOUR PRACTICAL JOB
EXERCISE SHEET No. 3.5.1/15 AND 3.5.1/16 MAY BE USED IN
ADDITION.
ACCORDING TO INSTRUCTORS' DECISION PLUG WIRING OR BOARD
INSTALLATION.

CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

DRAWING IS ALSO USED FOR EXERCISE EP 2.3/4.5.1/7

STAR-DELTA WITH CONTROL LAMPS

EP 1.3/3.5.1/17

Circuits III





DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

52





- a) WORK OUT YOUR DESCRIPTION OF CONTROL CIRCUITS 3.5.1/0
 b) EXPLAIN WHY DOES THE CONTROL CIRCUIT CROSS THE DIFFERENT CONTACTS.
 c) TAKE SUITABLE MATERIAL AND DO YOUR PRACTICAL JOB.
 EXERCISE SHEET No. 3.5.1/18 AND 3.5.1/20 MAY BE USED IN ADDITION.
 ACCORDING TO INSTRUCTORS DECISION PLUG WIRING OR BOARD INSTALLATION.
 CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.
 DRAWING IS ALSO USED FOR EXERCISE EP 2.3/4.5.1/8

MOTOR CONNECTION, 3~ STAR-DELTA REVERSING

EP 1.3/3.5.1/19


Contactors




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL





MOTOR CONNECTION, 3~2 SPEEDS
 TAPPED WOUND, 1 DIRECTION

EP 1.3/3.5.1/21

Contactors




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
 GENERAL

56



a) WORK OUT YOUR DESCRIPTION OF CONTROL CIRCUITS 3.5.1/0

b) TAKE SUITABLE MATERIAL AND DO YOUR PRACTICAL JOB.

EXERCISE SHEET No. 3.5.1/21 AND 3.5.1/23 MAY BE USED IN ADDITION.

WHY ARE TWO OVERLOAD PROTECTION SWITCHES INSTALLED ?

WHAT FOR IS THE INTERLINK SYSTEM PRACTISED ON SWITCHES AND CONTACTORS ?

ACCORDING TO INSTRUCTORS DECISION PLUG WIRING OR BOARD INSTALLATION.

CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

DRAWING IS ALSO USED FOR EXERCISE EP 2.3/4.5.1/9

MOTOR CONNECTION, 3~2 SPEEDS
TAPPED WOUND, 1 DIRECTION

EP 1.3/3.5.1/22

Contactors














DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING


PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

57



		
1 SWITCH, ON - OFF	2 SWITCH, REVERSING	3 SWITCH, STAR-DELTA
		
4 SWITCH, MULTI SPEED	5 CONTACTOR, ON-OFF	6 CONTACTOR, REVERSING
		
7 CONTACTOR, STAR-DELTA	8 CONTACTOR, Y-Δ-REVERSING	9 CONTACTOR, MULTI SPEED
LAYOUT		
 DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING PAK-GERMAN TECHNICAL TRAINING PROGRAMME		
EP 2.1/4.5.1/ Installation III ELECTRICIAN GENERAL 59		



MATERIAL:

- 1 Motor 3~ 380 V
- 3 Fuses (complete)
- 1 Drum Switch 3~ ON - OFF
- 1 Appliance Connection Box
- Cable
- Pipe
- Wire
- Clamps
- Screws
- Connectors

The motor 3~ 380 V is to be connected via fuses and switch.

Take fuses suitable for your motor.

All components are to be installed according to the given drawing and measurements.

Give estimate for the material.

(A suitable motor protection switch should be provided additionally, if available.)

CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

Exercise sheet,
No. 4.5.2/7 may be
used in addition

MOTOR CONNECTION, ON-OFF

EP 2.3/4.5.1/1


Installation III



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

**ELECTRICIAN
GENERAL**



The Motor 3~ 380 V is to be connected via fuses and reversing switch.

Take fuses suitable for your motor.

All components are to be installed according to the given drawing and measurements.

Give estimate for the material.

(A suitable motor protection switch should be provided additionally, if available.)

CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

Exercise sheet
No. 4.5.2/8 may be
used in addition

MOTOR CONNECTION, REVERSING

EP.2.3/4.5.1/2

Installation III




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

61



The three-phase motor 660 / 380 V is to be connected via fuses and star - delta switch.

Take fuses suitable for your motor.

All components are to be installed according to the given drawing and measurements.

Give estimate for the material.

(A suitable motor protection switch should be provided additionally, if available.)

CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

Exercise sheet
No. 4.5.2/9 may be
used in addition

MOTOR CONNECTION, STAR-DELTA

EP 2.3/4.5.1/3

Installation III




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

**ELECTRICIAN
GENERAL**

62



MATERIAL:

1 Motor 3~ 380 V
(Double Speed 4/8 P)

3 Fuses (complete)

1 Drum Switch 3~
Double Speed
(suitable for your
motor)

1 Appliance Connection
Box

Cable

Wire

Clamps

Screws

Connectors

Pipe

The three-phase double speed motor 380 V is to be connected via fuses and double speed switch.

Take fuses suitable for your motor.

All components are to be installed according to the given drawing and measurements.

Give estimate for material.

(A suitable motor protection switch should be provided additionally, if available.)

CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

Exercise sheet
No. 4.5.2/II may be
used in addition

MOTOR CONNECTION, DOUBLE SPEED

EP 2.3/4.5.1/4

Installation III




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

63



MATERIAL:

- 1 Motor 3~ 380 V
- 4 Fuses (complete)
- 1 Junction Box
- 1 Appliance Connection Box
- 3 Control Lamps (compl.)
- 1 Triple Push Button Switch (momentary contact)
- 2 Automatic Contactors
- 1 Therm. Motor Protection Switch (Overload Relay)
- Cable
- Pipe
- Wire
- Clamps
- Screws
- Connectors

Indicate number of wires in the installation layout.

The three-phase motor 380 V is to be connected via fuses, automatic contactor and therm. motor protection switch.

The control circuit consisting of fuse, triple push button switch, control lamps, automatic contactor coils as well as auxiliary contacts and therm. motor protection switch has to be installed as a separate circuit to the power (main) circuit.

All components are to be installed according to the given drawing and measurements.

Take fuses suitable for your motor.

Adjust also therm. protection switch.

Give estimate for material.

CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

Exercise sheet
No. 4.3 / 11/12+13 may
be used in addition

MOTOR CONNECTION, CONTACTOR REVERSING

EP 2.3/4.5.1/6


Installation III



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL



MATERIAL:

- 1 Motor 3~ 660/380 V
- 4 Fuses (complete)
- 1 Junction Box
- 1 Appliance Connection Box
- 2 Control Lamps (compl.)
- 1 Double Push Button Switch (momentary contact)
- 3 Automatic Contactors
- 1 Therm. Motor Protection Switch (Overload Relay)
- 1 Timing Relay (Timer)
- Cable
- Pipe
- Wire
- Clamps
- Screws
- Connectors

Indicate number of wires in the installation layout.

The three-phase motor 660/380 V is to be connected via fuses, automatic contactors and therm. motor protection switch.

The control circuit consisting of fuse, double push button switch, control lamps, timer, automatic contactor coils as well as auxiliary contacts and therm. motor protection switch has to be installed as a separate circuit to the power (main) circuit.

All components are to be installed according to the given drawing and measurements.

Take fuses suitable for your motor.

Adjust also therm. motor protection switch.

CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

Exercise sheet
No. 4, 5, 3/14, 15, 16 may
be used in addition

MOTOR CONNECTION CONTACTOR STAR DELTA

EP 2.3/4.5.1/7


Installation III



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL



MATERIAL:

- 1 Motor 3~ 660/380 V
- 4 Fuses (complete)
- 1 Junction Box
- 1 Appliance Connection Box
- 1 Control Lamp (complete)
- 1 Triple Push Button Switch (momentary contact)
- 4 Automatic Contactors
- 1 Therm. Motor Protection
- 1 Timing Relay (Timer)

Cable

Pipe

Wire

Clamps

Screws

Connectors

Indicate number of wires in the installation layout.

The three-phase motor 660/380 V is to be connected via fuses, automatic contactors and motor protection switch.

The control circuit consisting of fuse, triple push button switch, control lamp, timer, automatic contactor coils as well as auxiliary contacts and therm. motor protection switch has to be installed as a separate circuit to the power (main) circuit.

All components are to be installed according to the given drawing and measurements.

Take fuses suitable for your motor.

Adjust also therm. motor protection switch.

Give estimate for material.

CONNECT SUPPLY IN PRESENCE OF YOUR INSTRUCTOR.

Exercise sheet
No. 4.5.3/17.18+19 may
be used in addition

**MOTOR CONNECTION,
CONTACTOR STAR-DELTA REV.**

EP 2.3/4.5.1/8

Installation III



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

**ELECTRICIAN
GENERAL**

67

SERVICING ELECTRICAL MOTORS

DISMANTLING ELECTRICAL MOTORS

REMOVAL OF BALL BEARINGS

INSTALLING OF BEARINGS (2)

REMOVAL OF BUSHES AND SLEEVE BEARINGS

CLEANING OF BALL BEARINGS / TRANSPORTATION

SKIMMING OF ARMATURE

ASSEMBLING OF ELECTRICAL MOTORS

TEST SHEET (MECHANICAL)

TEST SHEET (ELECTRICAL)

CHECK LIST

TYPES OF BEARINGS

TYPES OF LUBRICATION NIPPLES

OIL SEALS

BEARINGS

PARTS OF ELECTRICAL MOTORS

CONSTRUCTION TYPES OF ELECTRICAL MOTORS

SEQUENCE OF OPERATION

1. Place all motor parts in a box !
2. Work very carefully to avoid damage.
3. Place motor on a clean, level and solid surface, e.g. work bench, concrete floor. Do not open the motor on dirt floor for dirt and dust will enter the motor and cause damage.
4. Clean the outside to remove all dirt and grease with a dry rag, cloth, duster or a brush and some petrol or kerosene oil. DO NOT USE WATER.
5. Mark the exact position of both the ENDSHIELDS and the MOTOR FRAME with a sharp centre punch, scriber or a file. This will help maintain the true bearing alignment when reassembling the motor and prevent mixing up the parts.



6. Take out carbon BRUSHES, if the motor has any, to avoid damaging them.
7. Open nuts or screws with the PROPER SPANNER, or correct size SCREWDRIVER. DO NOT USE PLIERS. If the screws or nuts are very tight, apply light hammer blows and soften with petrol or kerosene. ATTENTION: If the nuts or screws are firmly rusted the stud is likely to be twisted off.

8. Open ENDSHIELD on shaft extension side first. On the opposite side very often the motor lead wires are attached or the centrifugal switch is mounted. Be careful not to tear off the wires from the motor windings or damage the centrifugal switch.



9. Clean inside of the motor carefully with compressed air, rags etc. or a small paint brush with some petrol or kerosene oil. DO NOT USE WATER and do not use too much cleaning fluid directly on the windings as it may damage the insulation.

The use of sharp edged tools, e.g. screwdriver, scraper, knives, inside the motor is NOT permitted. For scratching use small pieces of wood or plastic only.

10. Place all parts of the motor in one box. Do not mix parts from other motors or tools with it. If parts are not kept in a box they will get lost resulting in an irreparable motor.

DISMANTLING ELECTRIC MOTORS

EP 2.3/4.5.6/1

Serv.E.Motors



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME


ELECTRICIAN

GENERAL


70

The ballbearing is removed from the shaft with a "puller".


Note: It is very important that only the ring which sits on the shaft is pressed by the puller.



Two strips of flat iron across a vice may be used to remove the bearing. Drive out the shaft with light hammer blows using protective pieces such as wood, copper or aluminium on the shaft end in order to prevent damage to the shaft.




Puller for removing ballbearings from bores.



Careful hammerblows on a piece of soft material, alu, wood etc., may be used to drive the bearing out.

Avoid excessive pressure on the inside ring for it may damage the bearing.



REMOVAL OF BALL BAERINGS

EP 2.3/4.5.6/2

Serv. E. Motors




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL


71



KEEP YOUR WORK-BENCH CLEAN


WRONG

PACKAGE SHOULD NOT BE OPENED AND NEW BEARING EXPOSED TO DIRT BEFORE BEING INSTALLED.



RIGHT


PACKAGE SHOULD BE KEPT CLEAN, AND BEARING SHOULD NOT BE REMOVED UNTIL NEEDED.



KEEP BEARINGS CLEAN
INSTALL BEARING PROPERLY

WRONG

BEARING SHOULD NOT BE DRIVEN ONTO SHAFT BY BLOWS ON OUTER CASE.



RIGHT

BEARING SHOULD BE LIGHTLY TAPPED ONTO SHAFT BY BLOWS ON TUBE WHICH FITS AGAINST INNER SLEEVE.

INSTALLING OF BEARINGS

EP 2.3/4.5.6/3

Serv. E. Motors



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME


ELECTRICIAN
GENERAL

72




DO NOT
TRY TO CLEAN
NEW BEARINGS


WRONG
THE OIL ON NEW BEARINGS MUST NOT
BE REMOVED.



RIGHT
THE NEW BEARINGS SHOULD BE FITTED IMMEDIATELY
AFTER ITS REMOVAL FROM THE PACKAGE.



WRONG
LOOSE COVER-PLATES PERMIT DIRT TO
ENTER HOUSINGS, CAUSING RAPID
BEARING FAILURE.



RIGHT
COVER-PLATES PROPERLY INSTALLED, PREVENTING
THE ENTRANCE OF DIRT.
PROTECT OPERATING BEARINGS

INSTALLING OF BEARINGS

EP 2.3/4.5.6/4

Serv. E. Motors



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING


PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL


73

Bushes are usually removed with a press and a suitable pressing tool, the same size as the bushes.

The pressing force can be applied with a press or hammer blows.



To press in and out bushes place endshields on firm support to avoid cracking or damage.





MOUNTING OF SLEEVE BEARINGS

ought to be done with a pressing motion of a correct size pressing tool only. If no press is available a vice can be used also.

For highest accuracy, especially for thin walled bearings, the bearing blank is first pressed into the endshields and then bored and reamed to size.

Check the right position of the lubricating hole. If necessary drill the hole after assembling the bearing.



REMOVAL OF BUSHES AND SLEEVE BEARINGS

EP 2.3/4,5,6/5

Serv. E. Motors



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING


PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

74

Cleaning a ball bearing

(not applicable for new bearings)



Clean with brush and kerosene or petrol.



Dry with a clean cloth.




Check if clean.




Apply protective oil film and wrap in clean cloth or paper till further use.





Check if clean.



Dry with compressed air.



Rinse with fresh petrol or kerosene.



Transportation of heavy motors

(lifting)

Attention: Prevent accidents.

Always secure load. Do not stand under lifted load.

CLEANING OF BALL BEARINGS TRANSPORTATION

EP 2.3/4.5.6/6

Serv.El.Motors



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME


ELECTRICIAN

GENERAL

75


1) MOUNT ROTOR BETWEEN CENTRES

- (1) shaft w. centre hole
- (2) dead centre
- (3) lathe dog
- (4) lubricant




2) CHECK TRUENESS WITH DIAL INDICATOR

(5)



3) CAREFULLY TURN LIGHT CUT

- (6) $\nabla = 35 \text{ m/min}$ 115 ft/min
- $\nabla \nabla = 30 \text{ m/min}$ 100 ft/min
- $\nabla = 0.3 - 0.5 \text{ mm/Rev.}$ 0.012 - 0.020"
- $\nabla \nabla = 0.05 - 0.1 \text{ mm/Rev.}$ 0.002 - 0.004"



4) SMOOTHEN WITH EMERY SHEET REMOVE ANY BURRS

- (7) smooth file
- (8) emery cloth



5) MICA INSULATION MUST BE BELOW THE SURFACE OF THE COMMUTATOR.


REMOVE THE INSULATING MATERIAL BETWEEN THE SEGMENTS WITH A SPEC. HACKSAW BLADE OF THE SAME THICKNESS !

- (9) hacksaw blade mind the winding!



6) TO SEAT THE CARBON BRUSH PROPERLY ON THE COMMUTATOR DRAW AN EMERY-SHEET BETWEEN BRUSH AND COMMUTATOR !

- (10) emery cloth
- (11) undercut mica



SKIMMING OF ARMATURE

EP 2.3/4.5.6/7

Serv.El.Motors



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN


GENERAL

76


In general the assembling of an E-motor is in the reversed order of the disassembling sequence.

NOTE:


- o Make sure that every part of the motor is clean and in good working order.
- o Fit the centrifugal switch carefully, if any.
- o Do not damage any motor windings.
- o Apply grease to ballbearings only immediately before final assembling.
- o The recess on the frame and the shoulder on the endshields MUST be clean and free from any deposit.



- o Dirt will cause misalignment.



- o Tighten bolts or nuts crosswise.
- o Use wooden hammer to tap endshields with light hammer blows while turning the shaft to obtain maximum alignment.



ASSEMBLING OF ELECTRIC MOTORS

EP 2.3/4.5.6/8

Serv. E. Motors



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

QUALITY CONTROL

All serviced and repaired motors are to be checked thoroughly both mechanically and electrically.

ONLY MOTORS IN PERFECT CONDITION ARE TO BE RELEASED!

Checklist: (mechanical)

	correct	tight too low (small)	loose too high (big)
1) Noise	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
2) End play	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
3) Rotor running free	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
4) Bearing fits	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
5) Lubrication, grease nipples, oil supply	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
6) Temperature bearings	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
7) Temperature motor frame	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
8) Condition of shaft, key way, pulley, bearing seals	<input type="checkbox"/>	(fair)	(unusable)
9) Bolts, nuts tightened	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
10) Test run 30 min.	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

Final remarks:

Signature/ Date

TEST SHEET (MECHANICAL)

EP 2.3/4.5.6/9

Serv.El.Motors



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GENERAL

78

QUALITY CONTROL

All serviced and repaired motors are to be checked thoroughly both mechanically and electrically.

ONLY MOTORS IN PERFECT CONDITION ARE TO BE RELEASED !

MANUFACTURER		
MOTOR NR	TYP	
YEAR OF CONST	SYST OF PROTECTION	
V	A	COS ϕ
RPM	Hz	HP
kW		

Type of motor: A.C. D.C. single phase polyphase

Checklist (electrical)

1) Fill in above type plate:

2) Measure and check: Voltage: _____ V
 Current _____ A
 Resistance: _____ Ω
 Revolution: _____ RPM
 Insulation:
 Earth: good too low too high

3) Temperature:	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
4) Noise:	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
5) Power output:	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
6) Testrun 30 min.:	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

Remarks:

 Sign / Date

TEST SHEET (ELECTRICAL)

EP2.3/4.5.6/10

Serv.El. Motors




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING


PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GÉNÉRAL

79






SLEEVE BEARINGS or BUSHES are turned from brass, gun metal bronze or special bearing metals. Sleeve bearing motors are usually oil lubricated and are generally used in horizontal position.

"OIL LESS" bushes are considered as permanently lubricated. In this arrangement the shaft passes through a sintered (powdered metal which is pressed and baked in an oven) bushing which has been impregnated with oil. No lubrication is needed. Used in fans etc.

ball bearing



BALL BEARINGS are manufactured from special steel and are precisely machined and ultra precisely ground. The balls and the actual running faces are highly polished.

SEALED BEARINGS contain lifetime lubrication and should not be opened.

ELECTRIC MOTORS TYPES OF BEARINGS

EP 2.3/4.5/6/12

Serv. El. Motors



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

81

LUBRICATION OF ELECTRIC MOTORS

Moving parts need to be lubricated to reduce friction which causes heat.

Heat may spoil the bearing.

Bearings in electric motors need a constant supply of clean oil or grease. The lubricant is supplied through specially designed oil supply holes commonly fitted with the following oil or grease nipples:


Form A



Form B




Form-C




ball-valve grease nipples

To be served with a grease gun only.


NOTE: clean nipples carefully before lubricating.



stauffer type
grease cup



oil nipple



oil nipple




wick oiler
(lubricator)

ADJUSTING SCREW



CONTROL
WINDOW

sight feed
lubricator



OIL CUP

OIL DEPOT

wick oiler
(lubricator)

TYPES OF LUBRICATION NIPPLES

EP 2.3/4.5.6/13

Serv.El.Motors



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING


PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN


GENERAL

82


NON CONTACTING OIL SEAL




CONVEYOR SPIRAL



LABYRINTH BOX




OIL THROWER




RETAINING RING


CONTACTING OIL SEAL




FELT RING SEAL



ELASTIC OIL SEAL



SEALED BALL BEARING



WATER PUMP SEAL

ELECTRIC MOTORS
OIL SEALS

EP 2.3/4.5.6/14

Serv.El.Motors




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING


PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN

GENERAL

83





مزید کتب پڑھنے کے لئے آج ہی وزٹ کریں : www.iqbalkalmati.blogspot.com

PARTS OF ELECTRIC-MOTOR

EP 2.3/4.5.6/16
Serv.El. Motors















































DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING


PAK-GERMAN TECHNICAL TRAINING PROGRAMME


ELECTRICIAN
GENERAL

85

THE VARIOUS TYPES OF CONSTRUCTION ARE DISTINGUISHED BY SYMBOLS, LETTER AND NUMBER.				
CLASS				
A	B	C	D	V
				
MACHINE WITHOUT SHAFT, FRAME WITH LEGS.	HORIZONTAL-SHAFT MACHINES WITH ENDSHIELD-BEARINGS	AS "B" BUT ADDITIONAL WITH PEDESTAL-BEARINGS.	HORIZONTAL-SHAFT MACHINES WITH PEDESTAL-BEARINGS.	VERTICAL-SHAFT MACHINES WITH GUIDE & RADIAL BEAR.
EXAMPLES OF THE MOST IMPORTANT MOTOR FORMS				
B 3	B 5	B 9	B 10	B 11
				
B 6	V 1	V 8	V 12	V 13
				
B 7	V 3	V 9	V 10	V 11
				
B 8	B 2	B 14	V 14	V 15
				
V 5	V 4	V 18	V 12	V 13
				
V 6	V 2	V 19	V 16	V 17
				
EXAMPLE: B 3 MOTOR WITH 2 ENDSHIELD BEARINGS, FRAME WITH LEGS, FREE SHAFT END SUITABLE FOR THE ATTACHMENT OF A PULLEY, PINION OR COUPLING. MOUNTING ON FOUNDATION, ETC.				
CONSTRUCTION TYPES OF ELECTRICAL MACHINES			EP 2.3/4.5.6/17 Serv. E. Motors	
DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING PAK-GERMAN TECHNICAL TRAINING PROGRAMME			ELECTRICIAN GENERAL	
			86	

		
<p>1 ASSEMBLY</p>	<p>2 SPOOL- PARTS</p>	<p>3 PAPER INSULATION</p>
		
<p>4 SPOOL ASSEMBLY</p>	<p>5 WINDINGS</p>	<p>6 CONNECTIONS</p>
 <p>ON DEMAND ONLY</p> <p>SAMPLE</p>	<p>The course "Repair of Windings" should actually consist of motor and transformer repairs as the need may arise for the Training Centre. In case no such work is available timely, the transformer shown on this layout is to be made. The following main skills are trained in this exercise :</p> <ol style="list-style-type: none"> 1) preparing spool body out of laminated paper 2) cutting insulation paper for different layers 3) winding coils, tapped and with different wire diameters 4) packing of iron core 5) fixing and connecting terminal plate 6) testing insulation and function <p>Parallel to the practical work all necessary informations (incl. calculations) are given in the theory lessons.</p>	
<p>7 LEGS/TERMINALS</p>		
	<p>LAYOUT</p>	
		<p>EP 2.1/4. 5. 5/ Repair of Winding</p>
	<p>DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING</p>	<p>ELECTRICIAN GENERAL</p>
	<p>PAK-GERMAN TECHNICAL TRAINING PROGRAMME</p>	<p>87</p>





SCALE 1:1

TRANSFORMER, SPOOL PARTS

EP 2. 3/4. 5. 5/2

Repair of Winding





DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

89






14

18


13 12



19

19

PART 19 PAPER, WHITE
80 gr / m² 86 DIN 827
OR EQUIVALENT



SCALE 1:1

TRANSFORMER SPOOL ASSEMBLY

EP. 2, 3/4, 5, 5/4

Repair of Winding




DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING


FAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

91



Mark the winding-tappings and ends properly (diff. colours, numbers etc)



TRANSFORMER WINDINGS

EP 2.3/4. 5.5/5

Repair of Winding





DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

92



TRANSFORMER CONNECTIONS

EP 2.3/4.5.5/6

Repair of Winding



DEVELOPMENT CELL FOR SKILLED LABOUR TRAINING

PAK-GERMAN TECHNICAL TRAINING PROGRAMME

ELECTRICIAN
GENERAL

93

